Scan-Antenna

Datasheet

DES-BH27

Coaxial Surge Protector 600 VDC (0-2700 MHz)

Coaxial Surge Protector to use for repeaters and full duplex radios.

• Simple and easy to install



ELECTRICAL SPECIFICATIONS

Туре	Coaxial Surge Protector
Frequency	0 - 2700 MHz
Impedance	50 Ohm
VSWR	<1.1:1 (0 -1000 MHz) <1.2:1 (1000 -2500 MHz) <1.4:1 (2500 - 2700 MHz)
Insertion Loss	< 0.1 dB
Discharge Voltage	Max. 600 V

MECHANICAL SPECIFICATIONS

Color	Silver
Dimensions	Ø31 x 55 mm
Weight	130 g
Operating Temperature	-40°C to +85°C
Connector	Type N-female
Cable	Not included
Serial No.	On product label

ORDERING INFORMATION

DES-BH27HH

In Box

SCAN ANTENNA A/S | LITERBUEN 15 | 2740 SKOVLUNDE | DENMARK | +45 +454333 1620 Disclaimer: Here you find all products for a complete antenna system. One-stop supplier with focus on high quality products produced in EU. No matter which type of antenna you are searching for, you will find it here. Every effort has been made to ensure the accuracy of the information in this product sheet. Scan Antenna reserves the right to introduce changes to this information without notice. All rights reserved.

Scan-Antenna®

Datasheet

PACKAGING INFORMATION

Туре

See "Part No."

SCAN ANTENNA A/S | LITERBUEN 15 | 2740 SKOVLUNDE | DENMARK | +45 +454333 1620 Disclaimer: Here you find all products for a complete antenna system. One-stop supplier with focus on high quality products produced in EU. No matter which type of antenna you are searching for, you will find it here. Every effort has been made to ensure the accuracy of the information in this product sheet. Scan Antenna reserves the right to introduce changes to this information without notice. All rights reserved.