Datasheet

CP-2-150

VHF 150 MHz 150 Watts Cavity Band Pass Filter

- For use in repeaters and full duplex radios.
- Single cavity.
- Easy tuning.

ELECTRICAL SPECIFICATIONS

Туре	VHF - Cavity Band Pass Filter
Frequency	136 - 174 MHz
Maximum Input Power	150 Watts
Insertion loss	≤ 0.5 - 2.0 dB
Attenuation	See diagram
VSWR	≤1:1.5
Impedance	50 Ohm



MECHANICAL SPECIFICATIONS

Color	Black Grey (RAL7021)
Dimension	15 x 15 x 60 cm + tuning screw
Weight	3.5 kg
Operating Temperature	-30°C to +60°C
Connector	Type N-female
Serial no.	On product label

ORDERING INFORMATION

CP-2-AQ Not tuned In Box	CP-2-AQ	Not tuned In Box
--------------------------	---------	---------------------

Printed: 8/23/2025

Datasheet

