Datasheet

# CP-80-150

## UHF 850 MHz 150 Watts Single Cavity Band Pass Filter

- For use in repeaters and full duplex radios.
- Single cavity.
- Easy tuning.

### **ELECTRICAL SPECIFICATIONS**

Туре	UHF - Single Cavity Band Pass Filter
Frequency	806 - 870 MHz
Maximum Input Power	150 Watts
Insertion loss	0.5 - 2.0 dB
Attenuation	тва
VSWR	≤ 1:1.5
Impedance	50 Ohm
Frequency Stability	9 ppm/°C (approx.)



#### MECHANICAL SPECIFICATIONS

Color	Black Grey (RAL7021)
Dimension	15 x 15 x 40 cm + tuning screw
Weight	2.0 kg
Operating Temperature	-30°C to +60°C
Connector	Type N-female
Serial no.	On product label

#### ORDERING INFORMATION

CP-80-AQ Not tuned In Box	CP-80-AQ	
---------------------------	----------	--