

PI-2

Flexible Helical Whip Antenna (134 - 240 MHz)

Flexible Helical whip antenna, especially made for use on portable transceivers.

- Wide range of different connector options available to connect to various transceivers
- Designed for Private Mobile Radios (PMR), such as Teltronic, Motorola, etc.
- Tunable to a specific frequency - see cutting diagram



ELECTRICAL SPECIFICATIONS

Type	Helical 1/4 λ Antenna
Frequency	135 - 175 MHz
Impedance	50 Ohm
VSWR	< 2.0 @ f.res.
Gain	0 dBd, 2.1 dBi
Polarisation	Vertical
Max. Input Power	25 W

MECHANICAL SPECIFICATIONS

Color	Black
Height	Max. 190 mm
Weight	Max. 40 g
Mounting Place	On transceivers etc.
Materials	PE, steel and copper
Operating Temperature	-40 to +70 °C

Datasheet

ORDERING INFORMATION

PI-2/BNC	Antenna with BNC-male
PI-2/TNC	Antenna with TNC-male
PI-2/BNC90°	Antenna with BNC-male-angle
PI-2/N	Antenna with Type N-male
PI-2/N90°	Antenna with Type N-male-angle
PI-2/PL	Antenna with UHF-male
PI-2/SMAM	Antenna with SMA-male

PACKAGING INFORMATION

Type	Polybag or bulk
------	-----------------



