Datasheet

# **PI-70C**

## Flexible Helical Whip Antenna (375 - 500 MHz)

Flexible Helical whip antenna, especially made for use on portable transceivers.

- Wide range of different connector options available to connect to various transceivers
- Designed for Private Mobile Radios (PMR), such as Teltronic, Motorola, etc.
- Tunable to a specific frequency see cutting diagram



### **ELECTRICAL SPECIFICATIONS**

Туре	Helical 1/4 λ Antenna
Frequency	375 - 500 MHz
Impedance	50 Ohm
VSWR	< 2.0 @ f.res.
Gain	0 dBd, 2.1 dBi
Polarisation	Vertical
Max. Input Power	25 W

### MECHANICAL SPECIFICATIONS

Color	Black
Height	Max. 100 mm
Weight	Max. 22 g
Mounting Place	On transceivers etc.
Materials	PE, steel and copper
Operating Temperature	-40 to +70 °C


Printed: 5/7/2024

Datasheet

## ORDERING INFORMATION

PI-70C/BNC	Antenna with BNC-male
PI-70C/TNC	Antenna with TNC-male
PI-70C/BNC90	Antenna with BNC-male-angle
PI-70C/N	Antenna with Type N-male
PI-70C/N90	Antenna with Type N-male-angle
PI-70C/PL	Antenna with UHF-male
PI-70C/SMAM	Antenna with SMA-male

## PACKAGING INFORMATION



Printed: 5/7/2024

Datasheet

