

# KITTIERRA (RG58)

## Grounding Kit for RG58

Coaxial Surge Protector to use for repeaters and full duplex radios.

- Simple and easy to install
- Grounding cable included
- For cable diameters:
  - Nominal: 1/2", 1/4", 3/8" & 5/8"
  - Maximum: 0.6"
  - Minimum: 0.1"

## ELECTRICAL SPECIFICATIONS

|              |               |
|--------------|---------------|
| Type         | Grounding Kit |
| Max. Current | 30 kA         |

## MECHANICAL SPECIFICATIONS

|                       |  |
|-----------------------|--|
| Color                 | Black  |
| Dimensions            | 152 x 76 x 58 mm                             |
| Weight                | 0.28 kg                                      |
| Operating Temperature | -40°C to +85°C                               |
| Ingress Protection    | IP68   |
| Materials             | PVC, Copper, Stainless Steel, Tin            |
| Contact               | Tinned Copper                                |
| Cable Jacket Removal  | Max. 2.3" (58.42 mm)<br>Min. 2.2" (55.88 mm) |
| Cable Diameter        | Max. 0.6" (15.24 mm)<br>Min. 0.1" (2.54 mm)  |

## ORDERING INFORMATION

|                |        |
|----------------|--------|
| KITTIERRA-RG58 | In bag |
|----------------|--------|

Datasheet

2 / 2

PACKAGING INFORMATION

|      |                |
|------|----------------|
| Type | See "Part No." |
|------|----------------|