

ADJUSTABLE P05/01 MAST MOUNT

Mounting Bracket with adjustable tilt

- Heavy duty bracket for installation of directional base station antennas on vertical pole
- For antenna boom diameter of \varnothing 30 - 35 mm.
- The bracket is mounted vertically overhead or on side of poles \varnothing 25 - 65 mm.
- Up to 50 degrees tilt
- Can be used for other antenna types, vertical and horizontal pole mounting
- Made from galvanized iron
- Stainless steel hardware included



MECHANICAL SPECIFICATIONS

| | |
|-------------------|--|
| Color | Silver |
| Mounting | On pole or rail with supplied U-bolts |
| Mounting place | On vertical pole or rail with diameter \varnothing 25 - 65 mm. |
| Materials | Bracket: Galvanized Iron Hardware: Stainless Steel |
| For Antenna Types | Directional antennas, Yagi and Dipole Boom diameter of \varnothing 30 - 35 mm |
| Dimension | 150 x 95 x 26 mm |
| Weight | 900 g (Mounting Hardware included) |



ORDERING INFORMATION

| | |
|----------------|------------------------------------|
| P05-HERRAJE/01 | Individually packing in Carton Box |
|----------------|------------------------------------|

PACKAGING INFORMATION

| | |
|--------|---|
| Type | Bulk packing or individually packing in Carton box (See "ORDERING INFORMATION") |
| Size | 275 x 185 x 53 mm |
| Weight | 1000 g |

