

HUNTER-68 (FME)

Semi-flexible reduced 1/4 λ centre-loaded portable whip antenna

Semi-flexible centre-loaded reduced 1/4 λ portable whip antenna with integrated FME-female connector, especially made for use on 4M-BAND transceivers used for hunting

- FME CONNECTOR ADAPTER SYSTEM FOR UNIVERSAL FITTING

ELECTRICAL SPECIFICATIONS

| | |
|------------------|-----------------------|
| Frequency | 64 - 74 MHz (4M-BAND) |
| Bandwidth | 10 MHz |
| Impedance | 50 ohm |
| Vswr | < 2.0 @ f.res. |
| Polarisation | Vertical |
| Gain | 0 dBd, 2.1 dBi |
| Max. Input Power | 25 W |

MECHANICAL SPECIFICATIONS

| | |
|-----------------------|---------------------------------------|
| Color | Black |
| Height | Approx. 560 mm |
| Weight | 30 g |
| Mounting Place | On transceivers |
| Materials | PC, glass-fibre, copper, PE and brass |
| Operating Temperature | -40C to +70C |
| Connector | FME-female |

ORDERING INFORMATION

| | |
|-----|--|
| P/N | 14252 (Antenna whip only) |
| P/N | 14252IP (Antenna whip only - Bulk packing) |



Datasheet

2 / 2

PACKAGING INFORMATION

| | |
|------|-----------------|
| Type | Polybag or bulk |
|------|-----------------|

