

HUNTER-68 (FME)

Semi-flexible reduced 1/4 λ centre-loaded portable whip antenna

Semi-flexible centre-loaded reduced 1/4 λ portable whip antenna with integrated FME-female connector, especially made for use on 4M-BAND transceivers used for hunting

- FME CONNECTOR ADAPTER SYSTEM FOR UNIVERSAL FITTING

ELECTRICAL SPECIFICATIONS

Frequency	64 - 74 MHz (4M-BAND)
Bandwidth	10 MHz
Impedance	50 ohm
Vswr	< 2.0 @ f.res.
Polarisation	Vertical
Gain	0 dBd, 2.1 dBi
Max. Input Power	25 W

MECHANICAL SPECIFICATIONS

Color	Black
Height	Approx. 560 mm
Weight	30 g
Mounting Place	On transceivers
Materials	PC, glass-fibre, copper, PE and brass
Operating Temperature	-40C to +70C
Connector	FME-female

ORDERING INFORMATION

P/N	14252 (Antenna whip only)
P/N	14252IP (Antenna whip only - Bulk packing)



Datasheet

PACKAGING INFORMATION

Type	Polybag or bulk
------	-----------------



The image shows a technical drawing of a long, thin antenna. A dimension line above the antenna indicates a length of 560. To the right, a detail view shows a circular cross-section with a diameter of Ø 12.